


Trek Model PD06087

High-Voltage Power Amplifier



The Model PD06087 is a DC-stable, high-voltage power amplifier used in industrial and research applications. It features an all-solid-state design for high slew rate, wide bandwidth and low-noise operation. The four-quadrant, active output stage sinks or sources current into reactive or resistive loads throughout the output voltage range. This type of output is essential to achieve an accurate output response and high slew rate demanded by a variety of loads such as highly capacitive or reactive loads. It is configured as a non-inverting amplifier.

Key Specifications

- Output Voltage Range: 0 to ± 5 kV DC or peak AC
- Output Current Range: 0 to ± 20 mA or peak AC
- Slew Rate: Greater than 500 V/ μ s
- Large Signal Bandwidth (1% distortion): DC to greater than 15 kHz
- DC Voltage Gain: Fixed at 1000 V/V

Typical Applications Include

- Electrophoresis
- Electrophotography
- Electrostatic deflection
- Electro-optic modulation
- AC or DC biasing

Features and Benefits

- Four-quadrant output for driving capacitive loads
- Closed loop system for high accuracy
- Short-circuit protected for equipment protection
- All solid-state design for maintenance free operation
- DC-stable for programmable supply applications
- Low output noise for ultra-accurate outputs
- NIST-traceable Certificate of Calibration provided with each unit
- CE compliant



TREK, INC. • 190 Walnut Street • Lockport, NY 14094 • USA • 800-FOR TREK
716-438-7555 • 716-201-1804 (fax) • www.trekinc.com • sales@trekinc.com

Model PD06087 Specifications

Performance

Output Voltage Range	0 to ± 5 kV DC or peak AC
Output Current Range	0 to ± 20 mA DC or peak AC
Input Voltage Range	0 to ± 5 V DC or peak AC
Input Impedance	20 k Ω , nominal
DC Voltage Gain	1000 V/V
DC Voltage Gain Accuracy	Better than 0.1% of full scale
DC Offset Voltage	Less than ± 2 V
Output Noise	Less than 5 V rms*
Slew Rate (10% to 90%, typical)	Greater than 500 V/ μ s
Large Signal Bandwidth (1% distortion)	DC to greater than 15 kHz
Small Signal Bandwidth (-3dB)	DC to greater than 20 kHz
Settling Time (to 1%)	Less than 100 μ s for a 0 to 5 kV step
Stability	
<i>Drift with Time</i>	Less than 100 ppm/hr, noncumulative
<i>Drift with Temp</i>	Less than 100 ppm/ $^{\circ}$ C

Voltage Monitor

Ratio	1/1000th of the high-voltage output
DC Accuracy	Better than 0.1% of full scale
DC Offset Voltage	Less than ± 3 mV
Output Noise	Less than 20 mV rms*
Output Impedance	47 Ω

Current Monitor

Ratio	0.5 V/ mA
DC Accuracy	Better than 1% of full scale
Offset Voltage	Less than ± 10 mV
Output Noise	Less than 30 mV rms*
Bandwidth (-3dB)	DC to greater than 5 kHz
Output Impedance	47 Ω

Features

High-Voltage On/Off	
<i>Local</i>	Individual push-button switch
<i>Remote (TTL compatible input)</i>	TTL high (or open) turns off high-voltage output. TTL low turns on high-voltage output.
Fault Status	A BNC provides a TTL low when the PD05034 is out of regulation for greater than 100 ms

Features (cont.)

Dynamic Adjustment	Graduated 1-turn panel potentiometer is used to optimize the AC response for various load parameters
Current Limit/Trip	Switch selectable for either limit or trip. Graduated 1-turn panel potentiometer is used to adjust limit or trip level from 0 to ± 20 mA
Out of Regulation Status	Illuminates and a TTL low is provided when unit fails to produce required HV output for 500 ms or more such as during current limit or short circuit conditions
Trip Status	Illuminates and a TTL low is provided when the high-voltage output is disabled due to the output current exceeding the current trip level, the detection of a high-voltage supply fault or the removal of the top cover

Mechanical

Dimensions	190 mm H x 432 mm W 417 mm D (7.5" H x 17" W x 16.4" D)
Weight	14.9 kg (31 lb)
HV Connector	Alden high-voltage connector
BNC Connectors	Amplifier Input, Voltage Monitor, Current Monitor, Remote High Voltage ON/OFF, Out of Regulation Status, Fault/Trip Status

Operating Conditions

Temperature	0 $^{\circ}$ C to 40 $^{\circ}$ C (32 $^{\circ}$ F to 104 $^{\circ}$ F)
Relative Humidity	To 85%, noncondensing
Altitude	To 2000 meters (6561.68 ft.)

Electrical

Line Voltage	Factory Set for one of two ranges: 104 to 127 V AC or 180 to 250 V AC, either at 48 to 63 Hz
AC Line Receptacle	Standard AC line connector with integral fuse holder
Power Consumption	680 VA, maximum

Supplied Accessories

Operators' Manual	PN: 23413
HV Output Cable	PN: 43406
Line Cord, Spare Fuses	PN: N5002; selected per geographic destination

Optional Accessories

High-voltage output cable	PN: 43421 (5 meter)
High-voltage output cable	PN: 43422 (10 meter)
High-voltage output cable	PN: 43423 (20 meter)
19-in Rack Mount Kit	Model 608RA (EIA hole spacing)
19-in Rack Mount Kit	Model 608RAJ (JIS hole spacing)

*Measured using the true rms feature of the HP Model 34401A digital multimeter

Copyright © 2012 TREK, INC. All specifications are subject to change. 1250/JRB

